SONY

VPL-DX100

2,300 lumens XGA Desktop projector



Overview

Cost effective 3LCD XGA data projector with 1024 x 768 dots resolution

The VPL-DX100 delivers convenient features for portable use, including a compact and lightweight design that is also energy-efficient, and a focus on lower total cost of operation. The data projector also delivers several powerful features shared across Sony's full line of business projectors. Sleek, compact styling and low weight make the VPL-DX100 perfect for portable use. It is also economically designed for optimum energy efficiency, thanks to its Auto Power Saving function with lamp control technology, energy-saving design, and long-lasting lamp.



Features

Compact, lightweight design

The VPL-DX100 has a compact and lightweight body with a small footprint of approximately $315 \times 75 \times 230.5$ mm ($12\ 13/32 \times 2\ 15/16 \times 9\ 1/16$ inches) and a light weight of approximately 2.5 kg ($5\ lb\ 7\ oz$).

Auto power saving functions

The brightness of the lamp's output is automatically adjusted depending on the brightness of the projected image, to avoid unnecessary power consumption. After 10 seconds of a static signal feed, the lamp dims by approximately 15%, which is hardly noticeable. If one of these projectors is left powered on while not in use, after a set period of time it will automatically detect no change of signal input and will dim the lamp to as low as approximately 30% of original brightness to significantly reduce energy consumption. The VPL-DX100 can also temporarily disable video signal output.

Long-lasting lamp and energy saving design

By incorporating high-performance lamp and advanced lamp-control technology, the VPL-DX100 offers a recommended lamp replacement time of 7,000 hours (in low mode). The VPL-DX100 offers remarkably low power consumption, allowing users to make significant savings on their electricity expenses. With a single push of the ECO MODE key on either the projector or the supplied Remote Commander™ unit, user can select an energy-saving setting from the ECO Mode menu.

RGB and HDMI inputs

VPL-DX100 includes a speaker (1 W) and a variety of interfaces (RGB, HDMI) that accept a variety of inputs signals.

Brilliant colour performance with 1.2x optical zoom lens

The VPL-DX100 adopts a 3LCD projection system incorporating three LCD panels. This system enables each projector to present bright and natural images. By combining an advanced generation of inorganic LCD panels that utilise Sony's BrightEraTM technology with a 3LCD projection system, the VPL-DX100 offers high picture quality and brightness.

12-bit 3D gamma correction and I/P conversion and film mode

The VPL-DX100 projector incorporates 12-bit 3D gamma correction circuitry to perform highly accurate gamma correction, achieving smoother gradations and a richer grey scale. Smooth, high-quality images are reproduced using a high performance processor for I/P conversion. Source signals suitable I/P conversion are processed automatically, and extremely accurate images are reproduced.

Closed captioning

Official teletext broadcasting, developed by the NCI, USA



Technical Specifications

Generic Specifications	
Display system	3 LCD system
Display device : Size of effective display area	0.63" (16.0 mm)
Display device : Number of pixels	XGA (1024 x 768)
Display device : Aspect ratio	4:3
Projection lens : Focus	Manual
Projection lens : Zoom > Powered / Manual	Manual
Projection lens : Zoom > Ratio	Approx. 1.2 x
Projection lens : Lens shift > Powered / Manual	-
Projection lens : Lens shift > Range > Vertical	-
Projection lens : Lens shift > Range > Horizontal	-
Projection lens : Throw ratio	1.47:1 to 1.77:1
Light source : Type	Lamp
Light source : Wattage	210 W type
Light source : System	-
 Recommended lamp replacement time(The figures are the expected maintenance time and not guaranteed. They will depend on the environment or how the projector is used): Lamp mode: High 	3000 H
• Recommended lamp replacement time(The figures are the expected maintenance time and not guaranteed. They will depend on the environment or how the projector is used): Lamp mode: Standard	5000 H
• Recommended lamp replacement time(The figures are the expected maintenance time and not guaranteed. They will depend on the environment or how the projector is used): Lamp mode: Low	7000 H
• Recommended lamp replacement time(With two lamp sequential use): Filter cleaning / replacement cycle(The figures are the expected maintenance time and not guaranteed. They will depend on the environment or how the projector is used) (Max.)	1000 H (cleaning)
Screen size	30" to 300"
Screen size	(0.76 m to 7.62 m)
Light output : Lamp mode: High	2300 lm
Light output : Lamp mode: Standard	1800 lm(The values are estimatel)
Light output : Lamp mode: Low	1500 lm(The values are estimatel)
Color light output : Lamp mode: High	2300 lm
Color light output : Lamp mode: Standard	1800 lm(The values are estimatel)
Color light output : Lamp mode: Low	1500 lm(The values are estimatel)
Contrast ratio (full white / full black)(This value is average)	2500:1
• Input : Composite video > BNC	-
• Input : Composite video > Pin Jack	1



https://computer > BRINC	Input: S video > Mini DIN 4-pin	-
	• Input : Computer > 5BNC	-
Input: DVIA (IPIDDP) Input: Audio > Pin alack (LIR) Input: Audio > Steroo mini jack Input: Audio (Works as an audio awtichref function, Output from a selected channel, not available in standby) > Steroo mini jack Input: Audio (Works as an audio awtichref function, Output from a selected channel, not available in standby) > Steroo mini jack Input: Audio (Works as an audio awtichref function, Output from a selected channel, not available in standby) > Steroo mini jack Input: Audio (Works as an audio awtichref function, Output from a selected channel, not available in standby) > Steroo mini jack Input: (Vo. Control, Others: IAM > Steroo mini jack, Pug in power DO S V Input: (Vo. Control, Others: IAM > Steroo mini jack, Pug in power DO S V Input: (Vo. Control, Others: ISB > Type A Input: (Vo. Control, Others:	Input : Computer > Mini D-sub 15-pin	1
Input: HOMI (HOCP)	Input : Component	-
Input: Audio > Pin Jack (L/R) Input: Audio > Stereo mini jack Input: Audio Stereo mini jack Input: Audio Stereo mini jack Input: Audio Works as an audio evoluther function. Output from a selected channel; not available in standby) > Stereo mini jack Input: Audio Works as an audio evoluther function. Output from a selected channel; not available in standby) > Stereo mini jack Input: Audio Output: Audio Stereo mini jack Pug in power DC 5 V Input: Input: Audio Stereo mini jack Pug in power DC 5 V Input: Inpu	Input : DVI-D (HDCP)	-
Input: Audio - Stereo mini jack Cytion board slot Cytion board slo	Input : HDMI (HDCP)	1
• Option board slot − • Cutput : Monitor's Mini D aub 15 pin − • Output : Audin(Workia as an audio switcher function. Output from a selected channel; not available in standby) > Stereo mini jack − • I/O, Control, Others : IRS 2920 > D sub 9-pin − • I/O, Control, Others : LAN > RL-46, 10BASE-T/10BBASE-TX − • I/O, Control, Others : IR (Control S) input > Stereo mini jack − • I/O, Control, Others : IR (Control S) output > Stereo mini jack − • I/O, Control, Others : IRS (Control S) output > Stereo mini jack − • I/O, Control, Others : IRS (Control S) output > Stereo mini jack − • I/O, Control, Others : IRS (Control S) output > Stereo mini jack − • I/O, Control, Others : IRS (Control S) output > Stereo mini jack − • I/O, Control, Others : IRS (Control S) output > Stereo mini jack − • I/O, Control, Others : IRS (Control S) output > Stereo mini jack − • I/O, Control, Others : IRS > Type A − • I/O, Control, Others : IRS (Sentrol S) output > Stereo mini jack − • I/O, Control, Others : IRS (Sentrol S) + − • I/O, Control, Others : IRS (Sentrol S) + − • Reyaltone consection (Max.) (D	Input : Audio > Pin Jack (L/R)	-
Output : Monitor > Minit D-sub 15-pin	Input : Audio > Stereo mini jack	1
Output : Audio(Works as an audio switcher function. Output from a selected channel; not available in standby) > Stereo mini jack	Option board slot	-
	Output : Monitor > Mini D-sub 15-pin	_
	Output : Audio(Works as an audio switcher function. Output from a selected channel; not available in standby) > Stereo mini jack	-
№ 1/O, Control, Others : IR (Control S) input > Stereo mini jack. — № 1/O, Control, Others : IR (Control S) output > Stereo mini jack. — № 1/O, Control, Others : USB > Type A — № 1/O, Control, Others : Wisrophone input > Mini jack — № 1/O, Control, Others : Wisrophone input > Mini jack — № 1/O, Control, Others : Wireless — • Speaker 1 Wx 1 (monaural) • Keystone correction (Max.)(Depends on resolution) : Vertical +/- 30° • Keystone correction (Max.)(Depends on resolution) : Horizontal — • Power requirements AC 100 V to 240 V • Power requirements 22 9 A to 12 A, 5060 Hz • Power consumption : AC 100 V to 120 V > Lamp mode: High 275 W • Power consumption : AC 100 V to 120 V > Lamp mode: High 288 W(The values are estimatel) • Power consumption : AC 220 V to 240 V > Lamp mode: High 268 W • Power consumption : AC 220 V to 240 V > Lamp mode: Standard 221 W(The values are estimatel) • Power consumption : AC 220 V to 240 V > Lamp mode: Standard 228 W(The values are estimatel) • Power consumption : AC 220 V to 240 V > Lamp mode: Standard 229 W(The values are estimatel) • Power consumption : AC 220 V to 240 V > Lam	• I/O, Control, Others: RS-232C > D-sub 9-pin	-
• I/O, Control, Others : IR (Control S) output > Stereo mini jack − • I/O, Control, Others : USB > Type A − • I/O, Control, Others : USB > Type B − • I/O, Control, Others : Microphone input > Mini jack − • I/O, Control, Others : Wireless − • Spaaker 1 W x 1 (monatural) • Keystone correction (Max.)(Depends on resolution) : Vertical +/-30° • Keystone correction (Max.)(Depends on resolution) : Horizontal − • Power requirements AC 100 V to 240 V • Power requirements 2.9 A to 1.2 A, 50/60 Hz • Power consumption : AC 100 V to 120 V > Lamp mode: Standard 228 W(The values are estimate) • Power consumption : AC 100 V to 120 V > Lamp mode: Standard are estimate) • Power consumption : AC 220 V to 240 V > Lamp mode: Standard 221 W(The values are estimate) • Power consumption : AC 220 V to 240 V > Lamp mode: Standard 221 W(The values are estimate) • Power consumption : AC 220 V to 240 V > Lamp mode: Standard 221 W(The values are estimate) • Power consumption : AC 220 V to 240 V > Lamp mode: Standard are estimate) • Power consumption : AC 220 V to 240 V > Lamp mode: Standard are estimate) • Power consumption : AC 220	• I/O, Control, Others : LAN > RJ-45, 10BASE-T/100BASE-TX	-
• I/O, Control, Others : USB > Type A − • I/O, Control, Others : USB > Type B − • I/O, Control, Others : Microphone input > Mini jack − • I/O, Control, Others : Wireless − • Speaker 1 W x 1 (monaural) • Keystone correction (Max.)(Depends on resolution) : Vertical +/- 30° • Keystone correction (Max.)(Depends on resolution) : Horizontal − • Power requirements AC 100 V to 240 V • Power consumption : AC 100 V to 120 V > Lamp mode: High 275 W • Power consumption : AC 100 V to 120 V > Lamp mode: Standard 228 W(The values are estimatel) • Power consumption : AC 200 V to 240 V > Lamp mode: High 263 W • Power consumption : AC 220 V to 240 V > Lamp mode: High 223 W(The values are estimatel) • Power consumption : AC 220 V to 240 V > Lamp mode: High 221 W(The values are estimatel) • Power consumption : AC 220 V to 240 V > Lamp mode: Standard 221 W(The values are estimatel) • Power consumption : AC 220 V to 240 V > Lamp mode: Low 189 W(The values are estimatel) • Power consumption : AC 220 V to 240 V > Lamp mode: Low 189 W(The values are estimatel) • Power consumption : AC 220 V to 240 V > Lamp mode: Low 189 W(The values are estimatel)	 I/O, Control, Others: IR (Control S) input > Stereo mini jack, Plug in power DC 5 V 	-
I/O, Control, Others : USB > Type B I/O, Control, Others : Microphone input > Mini jack I/O, Control, Others : Wireless I/O, Control, Others : Wireless Speaker I/O (Androl, Others : Wireless) Keystone correction (Max.)(Depends on resolution) : Vertical Keystone correction (Max.)(Depends on resolution) : Horizontal Power requirements Power requirements Power consumption : AC 100 ∨ to 120 ∨ > Lamp mode: High Power consumption : AC 100 ∨ to 120 ∨ > Lamp mode: Standard Power consumption : AC 100 ∨ to 120 ∨ > Lamp mode: Low Power consumption : AC 220 ∨ to 240 ∨ > Lamp mode: High Power consumption : AC 220 ∨ to 240 ∨ > Lamp mode: Standard Power consumption : AC 220 ∨ to 240 ∨ > Lamp mode: Standard Power consumption : AC 220 ∨ to 240 ∨ > Lamp mode: Standard Power consumption : AC 220 ∨ to 240 ∨ > Lamp mode: Standard Power consumption : AC 220 ∨ to 240 ∨ > Lamp mode: Standard Power consumption : AC 220 ∨ to 240 ∨ > Lamp mode: Low Restimately Power consumption : AC 220 ∨ to 240 ∨ > Lamp mode: Low Restimately Power consumption : AC 220 ∨ to 240 ∨ > Lamp mode: Low Restimately	 I/O, Control, Others : IR (Control S) output > Stereo mini jack 	-
IVO, Control, Others: Microphone input > Mini jack IVO, Control, Others: Wireless IWx 1 (monaural) Keystone correction (Max.)(Depends on resolution): Vertical Keystone correction (Max.)(Depends on resolution): Horizontal Newstone correction (Max.)(Depends on resolution): Horizontal Power requirements AC 100 V to 240 V Power requirements Power consumption: AC 100 V to 120 V > Lamp mode: High Power consumption: AC 100 V to 120 V > Lamp mode: Standard Power consumption: AC 100 V to 120 V > Lamp mode: High Power consumption: AC 220 V to 240 V > Lamp mode: High Power consumption: AC 220 V to 240 V > Lamp mode: High Power consumption: AC 220 V to 240 V > Lamp mode: Standard Standard Power consumption: AC 220 V to 240 V > Lamp mode: High Power consumption: AC 220 V to 240 V > Lamp mode: Standard Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Standard Standard Standard Standard Standard Standard Standard	• I/O, Control, Others : USB > Type A	-
I/O, Control, Others: Wireless Speaker 1 W x 1 (monaural) Keystone correction (Max.)(Depends on resolution): Vertical Keystone correction (Max.)(Depends on resolution): Horizontal Power requirements AC 100 V to 240 V 9 Power requirements Power consumption: AC 100 V to 120 V > Lamp mode: High Power consumption: AC 100 V to 120 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: High Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low	• I/O, Control, Others : USB > Type B	-
Speaker Keystone correction (Max.)(Depends on resolution): Vertical Keystone correction (Max.)(Depends on resolution): Horizontal Power requirements AC 100 V to 240 V Power requirements Power requirements Power consumption: AC 100 V to 120 V > Lamp mode: High Power consumption: AC 100 V to 120 V > Lamp mode: Standard Power consumption: AC 100 V to 120 V > Lamp mode: High Power consumption: AC 100 V to 120 V > Lamp mode: Standard Power consumption: AC 100 V to 120 V > Lamp mode: High Power consumption: AC 220 V to 240 V > Lamp mode: High Power consumption: AC 220 V to 240 V > Lamp mode: High Power consumption: AC 220 V to 240 V > Lamp mode: High Power consumption: AC 220 V to 240 V > Lamp mode: High Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: Low	 I/O, Control, Others: Microphone input > Mini jack 	-
Keystone correction (Max.)(Depends on resolution) : Vertical Keystone correction (Max.)(Depends on resolution) : Horizontal Power requirements AC 100 V to 240 V Power requirements 2.9 A to 1.2 A, 50/60 Hz Power consumption : AC 100 V to 120 V > Lamp mode: High Power consumption : AC 100 V to 120 V > Lamp mode: Standard Power consumption : AC 100 V to 120 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: High Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: High Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low Power consumption : AC 220 V to 240 V > Lamp mode: Low	• I/O, Control, Others : Wireless	-
Keystone correction (Max.) (Depends on resolution): Horizontal Power requirements AC 100 V to 240 V Power requirements Power consumption: AC 100 V to 120 V > Lamp mode: High Power consumption: AC 100 V to 120 V > Lamp mode: Standard Power consumption: AC 100 V to 120 V > Lamp mode: Standard Power consumption: AC 100 V to 120 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: High Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Standby mode power consumption: AC 100 V to 120 V > Standard	Speaker	1 W x 1 (monaural)
Power requirements Power consumption: AC 100 V to 120 V > Lamp mode: High Power consumption: AC 100 V to 120 V > Lamp mode: Standard Power consumption: AC 100 V to 120 V > Lamp mode: Standard Power consumption: AC 100 V to 120 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: High Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Standby mode power consumption: AC 100 V to 120 V > Standard Standby mode power consumption: AC 100 V to 120 V > Standard Standby mode power consumption: AC 100 V to 120 V > Standard	Keystone correction (Max.)(Depends on resolution) : Vertical	+/- 30°
Power consumption: AC 100 V to 120 V > Lamp mode: High Power consumption: AC 100 V to 120 V > Lamp mode: Standard Power consumption: AC 100 V to 120 V > Lamp mode: Standard Power consumption: AC 100 V to 120 V > Lamp mode: Low Power consumption: AC 100 V to 120 V > Lamp mode: Low Power consumption: AC 220 V to 240 V > Lamp mode: High Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Low Standby mode power consumption: AC 100 V to 120 V > Standard Standby mode power consumption: AC 100 V to 120 V > Standard	Keystone correction (Max.)(Depends on resolution) : Horizontal	-
Power consumption : AC 100 V to 120 V > Lamp mode: High Power consumption : AC 100 V to 120 V > Lamp mode: Standard Power consumption : AC 100 V to 120 V > Lamp mode: Standard Power consumption : AC 100 V to 120 V > Lamp mode: Low 195 W(The values are estimatel) Power consumption : AC 220 V to 240 V > Lamp mode: High Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: Low Standby mode power consumption : AC 100 V to 120 V > Standard Standby mode power consumption : AC 100 V to 120 V > Standard - Standby mode power consumption : AC 100 V to 120 V > Standard	Power requirements	AC 100 V to 240 V
Power consumption : AC 100 V to 120 V > Lamp mode: Standard Power consumption : AC 100 V to 120 V > Lamp mode: Low 195 W(The values are estimatel) Power consumption : AC 220 V to 240 V > Lamp mode: High Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: Low 189 W(The values are estimatel) Standby mode power consumption : AC 100 V to 120 V > Standard Standby mode power consumption : AC 100 V to 120 V > Standard	Power requirements	
Power consumption : AC 100 V to 120 V > Lamp mode: Low 195 W(The values are estimatel) Power consumption : AC 220 V to 240 V > Lamp mode: High Power consumption : AC 220 V to 240 V > Lamp mode: High Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: Low 189 W(The values are estimatel) Standby mode power consumption : AC 100 V to 120 V > Standard Standby mode power consumption : AC 100 V to 120 V > Standard	 Power consumption : AC 100 V to 120 V > Lamp mode: High 	275 W
Power consumption : AC 220 V to 240 V > Lamp mode: High Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: Standard Power consumption : AC 220 V to 240 V > Lamp mode: Low 189 W(The values are estimatel) Standby mode power consumption : AC 100 V to 120 V > Standard - Standby mode power consumption : AC 100 V to 120 V > Standard	 Power consumption : AC 100 V to 120 V > Lamp mode: Standard 	*
Power consumption: AC 220 V to 240 V > Lamp mode: Standard Power consumption: AC 220 V to 240 V > Lamp mode: Low 189 W(The values are estimatel) Standby mode power consumption: AC 100 V to 120 V > Standard - Standby mode power consumption: AC 100 V to 120 V > Standard	 Power consumption : AC 100 V to 120 V > Lamp mode: Low 	
Power consumption : AC 220 V to 240 V > Lamp mode: Low 189 W(The values are estimatel) Standby mode power consumption : AC 100 V to 120 V > Standard -	Power consumption : AC 220 V to 240 V > Lamp mode: High	263 W
Power consumption : AC 220 V to 240 V > Lamp mode: Low Standby mode power consumption : AC 100 V to 120 V > Standard Standby mode power consumption : AC 100 V to 120 V > Standard	Power consumption : AC 220 V to 240 V > Lamp mode: Standard	
Standby mode power consumption : AC 100 V to 120 V > Standard —	Power consumption : AC 220 V to 240 V > Lamp mode: Low	
Standby mode power consumption : AC 100 V to 120 V > Low	Standby mode power consumption : AC 100 V to 120 V > Standard	
	Standby mode power consumption : AC 100 V to 120 V > Low	
Standby mode power consumption : AC 220 V to 240 V > Standard —	Standby mode power consumption : AC 220 V to 240 V > Standard	_



Standby mode power consumption : AC 220 V to 240 V > Low	
Heat dissipation : AC 100 V to 120 V	939 BTU
Heat dissipation : AC 220 V to 240 V	898 BTU
Dimensions (W x H x D) (without protrusions)	315 x 75 x 230.5 mm
Dimensions (W x H x D) (without protrusions)	12 13/32 x 2 15/16 x 9 1/16 in
Mass	2.5 kg / 5 lb 7 oz
Supplied accessories : Remote commander	RM-PJ8
Supplied accessories : Wireless LAN Module	-
Optional accessories : Replacement lamp	LMP-D213
Optional accessories : Projection lenses	-
Optional accessories : Projection lens adapter	-
Optional accessories : Interactive pen device	-
Optional accessories : Wireless LAN Module	-



Accessories

Lamps



LMP-D213

Replacement Lamp for the VPL-D100 Series