# HP LaserJet Pro MFP M130fw



Keep things simple with a compact HP LaserJet Pro powered by JetIntelligence Toner cartridges. Print professional documents from a range of mobile devices, plus scan, copy, fax, and help save energy with a wireless MFP designed for efficiency.



**Printspeed:** Letter: Up to 23 ppm black; First Page Out: As fast as 7.3 sec black;

**Print Resolution:** Black (best): Up to 600 x 600 dpi, HP FastRes 1200 (1200 dpi quality)

**Print Technology Resolution:** HP FastRes 600, HP FastRes

Standard Connectivity: Hi-Speed USB 2.0 port (device); builtin Fast Ethernet 10/100Base-TX network port; Phone line port (in/out), wireless

Standard Memory: Standard: 256 MB

Mobile Printing Capability: HP Smart app; Apple AirPrint<sup>™</sup>; HP ePrint; Google Cloud Print 2.0; Mopria-certified; Wi-Fi Direct Paper Handling: 150-sheet input tray; 100-sheet output tray Display: 2.7-in touch screen, LCD (color graphics)













### Designed for efficiency

- Print, scan, copy, and fax with a compact HP LaserJet MFP that fits into tight workspaces.
- Wait less. Print up to 23 pages per minute, with first pages ready in as fast as 7.3 seconds.6
- Help save energy with HP Auto-On/Auto-Off Technology.7
- Tackle tasks and scan to email, USB, and network folders from the 2.7-inch (6.9 cm) color touchscreen.8

## Mobile printing made simple

- Get simple setup, and print and scan from your phone, with the HP Smart app.<sup>3</sup>
- Easily print from a variety of smartphones and tablets.9
- Print directly from your mobile device to your Wi-Fi Direct<sup>®</sup> printer—without accessing the company network <sup>4</sup>
- HP Voice-activated printing—your HP printer works with Amazon Alexa, Google Assistant, Microsoft Cortana.<sup>5</sup>

### HP quality—print after print


- Produce sharp text, bold blacks, and crisp graphics with precision black toner.
- Don't be fooled by alternatives that mimic Original HP. Help ensure you're getting the quality you paid for.
- Track toner levels with print gauge technology<sup>10</sup>—produce the most prints possible and get what you paid for.
- No delays or mess—quickly replace your cartridges, using auto seal removal and easy-open packaging.

<sup>&</sup>lt;sup>1</sup> App or software and HP ePrint account registration also may be required. Some features require purchase of an optional accessory. Learn more at http://www.hp.com/go/mobileprinting <sup>2</sup> Printing speed measured using ISO/IEC 24734 and excludes first set of test documents. Exact speed versus predecessor varies depending on the system configuration, software application, driver, and document complexity. Learn more at http://www.hp.com/go/printerclaims. <sup>3</sup> Requires the HP Smart app download. Features controlled may vary by mobile device operating system. Full list of supported operating systems and details at http://support.hp.com/us-en/document/c03561640. For details on local printing requirements see http://hp.com/go/mobileprinting. <sup>4</sup> Mobile device needs to be connected directly to the signal of a Wi-Fi Direct's supported MP or printer prior to printing. Depending on mobile device, an app or driver may also be required. For details, see http://www.hp.com/go/mobileprinting. Wi-Fi Direct is a registered trademark of Wi-Fi Alliance\*. <sup>5</sup> Requires Amazon Alexa, Google Assistant, or Microsoft Cortana and an HP web-connected printer registered with Google Cloud Print or ePrint. For ePrint account registration, see http://www.hp.com/go/support/eprint. <sup>6</sup> Measured using ISO/IEC 17625. Exact speed varies depending on the system configuration, software application, driver, and document complexity. Learn more at http://www.hp.com/go/printerclaims. <sup>7</sup> HP Auto-On/Auto-Off Technology capabilities are subject to printer and settings. <sup>8</sup> Requires an Internet connection to the printer. Services may require registration. App availability varies by country, language, and agreements. For details, see hpconnected.com. <sup>9</sup> For details on local printing requirements see http://hp.com/go/mobile printing. <sup>10</sup> As compared with cartridge gauges for HP predecessor products.

# HP LaserJet Pro MFP M130fw Specifications Table

Functions / Multitasking	Print, copy, scan, fax / Yes	What's in the box	G3Q60A HP LaserJet Pro MFP M130fw; HP Black LaserJet Toner Cartridge ~700 pages
Supported			GSQOATHE Caselet His Hire History, he black casels et intelled artifage 4700 pages, Hasel et Imaging Drum ~12,000 pages; Power cord; Phone cord; USB cable; Getting started guide; Set up poster; Support flyer; Printer documentation and software on CD-ROM; Errata, declaration (some countries)
Print Speed	Letter: Up to 23 ppm; First Page Out Black: As fast as 7.3 sec		
Print Resolution	<b>Black (best)</b> : Up to 600 x 600 dpi, HP FastRes 1200 (1200 dpi quality)	Replacement Cartridges <sup>5</sup>	HP 17A Original Black LaserJet Toner Cartridge CF217A(~1600), HP 19A Original
Print Technology	Laser		LaserJet Imaging Drum CF219A(~12000).
Print Resolution Technologies	HP FastRes 600, HP FastRes 1200	Product Dimensions	<b>W x D x H</b> : 16.66 x 11.34 x 11 in; <b>Maximum</b> : 16.66 x 20.13 x 16.68 in
Print Cartridges Number	1 Black	Product Weight	16.76 lb
Standard Print languages	PCLmS, URF, PWG	Warranty Features	one year limited warranty
Printer Smart Software Features	HP ePrint, Apple AirPrint™, Instant-on Technology, HP Auto-On/Auto-Off, JetIntelligence cartridges; HP Smart App	Energy Efficiency Compliance	ENERGY STAR® qualified
Scan Type / Technology	ADF, Flatbed/ CIS	Control Panel	2.7 in touch screen, LCD (color graphics)
Scan Resolution	Hardware: Up to 300 x 300 dpi (color and mono, ADF); Up to 600 x 600 dpi (color, flatbed); Up to 1200 x 1200 dpi (mono, flatbed); <b>Optical:</b> Up to 300 dpi (color and mono, ADF); Up to 600 dpi (color, flatbed); Up to 1200 dpi (mono, flatbed)	Display Description Software Included	2.7 in touch screen, LCD (color graphics) For Windows OS: HP Software Installer, HP Software Uninstaller (exclude Win8+), HP PCLmS Printer Driver, HP Device Experience (DXP), HP Web Services Assist (HP Connected), Device Setup & Software, Online user manuals, HP Printer Assistant, HP Scan Driver, HP Scan Application, HP Fax Driver (4:1 bundle only), HP Fax Application (4:1 bundle only), HP Product Improvement Study, For Mac OS: Welcome Screen, (Directs users to HP.com or OS App Source for LaserJet Software)
Scan File Format	JPEG, PDF, PNG		
Scan Input Modes	Front control panel, scanning via HP LaserJet Scan (Windows®); HP Director (Macintosh) or TWAIN-compliant or WIA-compliant software		
Scan Size Maximum	<b>ADF</b> : 8.5 x 11.7 in; <b>Flatbed</b> : 8.5 x 11.7 in	Compatible Operating Systems <sup>18</sup>	Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer; Windows Vista®: (32-bit only), 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8; Windows® XP SP3 or higher (32-bit only); any Intel® Pentium® II, Celeron® or 233 MHz compatible processor, 850 MB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8; Apple® OS X EI Capitan (v10.11) OS X Yosemite (v10.10) OS X Mavericks (v10.9), OS X Mountain Lion (v10.8); 1 GB HD; Internet required; USB; Linux (For more information, see http://hplipopensource.com/hplip-web/index.html)
Scan Speed <sup>16</sup>	Up to 11 ppm		
Scanner Advanced Features	No		
Bit Depth / Grayscale levels	24-bit/ 256		
Digital Sending Standard Features	Scan to email; Scan to network folder		
Copy Resolution	<b>Black (text and graphics)</b> : 600 × 400 dpi; 600 × 400 dpi		
Maximum Number Of Copies	Up to 99 copies	Compatible Network Operating Systems	Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer; Windows Vista®; (32-bit only), 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer B; Windows® XP SP3 or higher (32-bit only); any Intel® Pentium® II, Celeron® or 233 MHz compatible processor, 850 MB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer B; Apple® 05 X El Capitan (v10.11) OS X Yosemite (v10.10) OS X Mavericks (v10.9), OS X Mountain Lion (v10.8); 1 GB HD; Internet required; USB; Linux (For more information, see http://hpliopensource.com/hplib-webfindex.html)
Copier Resize	25 to 400%		
Copier Settings	Number of Copies; Lighter/Darker; Optimize; Paper; Multi-Page Copy; Draft Mode		
Fax Speed <sup>15</sup>	Up to: 4.2 kB/s; Letter: 3 sec per page		
Fax Resolution	<b>Black (best)</b> : Up to $300 \times 300$ dpi (halftone enabled); <b>Black (standard)</b> : $203 \times 98$ dpi		
Fax Smart Software Features	No		
Fax Features  Standard Connectivity	Fax Memory. Up to 1000 pages; Auto Fax Reduction Supported: Yes; Auto-Redialing. Yes; Fax Delayed Sending: Yes; Distinctive Ring Detection Supported: Yes; Fax Forwarding Supported: Yes; Fax Polling Supported: Yes; Fax Polling Supported: Yes; Maximum Speed Dialing Numbers: Up to 120 numbers (119 group dials); PC Interface Supported: Yes; Maximum Speed Dialing Numbers: Up to 120 numbers (119 group dials); PC Interface Supported: Yes; Remote Retrieval Capability Supported: No; Telephone Handset Supported: Yes; Hi-Speed USB 2.0 port (device); built-in Fast Ethernet 10/100Base-TX network port;	Minimum System Requirements	PC. Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer; Windows Vista®: (32-bit only), 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8; Windows® XP SP3 or higher (32-bit only): any Intel® Pentium® II, Celeron® or 233 MHz compatible processor, 850 MB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8; MAC: Apple®OS X EI Capitan (v10.11) OS X Yosemite (v10.10) OS X Mavericks (v10.9) 1 GB HD; Internet required; USB
	Phone line port (in/out), wireless	Power <sup>2</sup>	Power Supply Type: Internal; Power Requirements: 110-volt input voltage: 110 to 127 VAC (+/- 10%), 60 Hz/50 Hz, 4.8 A; 220-volt input voltage: 220 to 240 VAC (+/- 10%), 60 Hz/50 Hz, 2.8 A; Power Consumption: 255 watts (active printing), 4.2 watts (ready), 1.0 watts (sleep), 0.7 watts (Auto Off/Wake on USB, enabled at shipment)
Network Capabilities	10/100 Ethernet		
Network Ready	Standard (built-in Ethernet, Wi-Fi 802.11b/g/n)		
Wireless Capability	Standard (Wi-Fi 802.11b/g/n)	Acoustics	Acoustic Power Emissions: 6.5 B(A) (printing at 23 ppm)
Mobile Printing Capability <sup>8</sup>	Apple AirPrint™; HP ePrint; Google Cloud Print 2.0; Mopria-certified; Wi-Fi Direct; HP Smart App	Operating Environment	Operating Temperature Range: 59 to 90.5°F; Recommended Operating Temperature: 63.5 to 77°F; Storage Temperature Range: -4 to 140°F; Non-Operating Humidity Range: 10 to 90% RH; Operating Humidity Range: 10 to 80% RH; Recommended Humidity Operating Range: 30 to 70% RH; Operating Range: 30 to 70% RH; Recommended Humidity Operating Range: 30 to 70% RH; Recommended RH
Memory	Standard: 256 MB; Maximum: 256 MB		
Processor Speed	600 MHz / <b>Hard disk:</b> No		Harrialty operating range. 30 to 70% ft/1
Duty Cycle <sup>9</sup>	Monthly, letter: Up to 10,000 pages	Learn more at	
Recommended Monthly Page Volume <sup>10</sup>	150 to 1500	hp.com	
Media Types Supported	Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, postcards		
Media Weight Supported	16 to 43 lb		
Media Sizes Supported	Letter; legal; executive; 8.5 x 13 in; envelopes		
Media Sizes Custom	3 x 5 to 8.5 x 14 in		
Paper Handling	150-sheet input tray; 100-sheet output tray; <b>Duplex Options</b> : Manual duplex; <b>Auto</b>		

Introductory HP Black LaserJet Toner Cartridge (~700 pages), HP Original LaserJet Imaging Drum (~12,000 pages). Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/learnaboutsupplies <sup>2</sup> Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Penery Star value typically based on measurement of 115 V device. <sup>4</sup> Based on the Ba TEC mental will be absed on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Penery Star value typically based on measurement of 615 V device. <sup>4</sup> Based on the Ba TEC mental will be believed in the Ba TEC mental will be beauting voltages. This will device and the product warranty. Penery Star value typically based on measurement of 615 V device. <sup>4</sup> Based on the Ba TEC mental will be beauting voltages. This will be product warranty. Penery Star value typically based on measurement of 615 V device. <sup>4</sup> Based on the Ba TEC mental will be will be printed and other factors. For details see http://www.hp.com/go/learnaboutsupplies. This will be product value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/learnaboutsupplies. This will be product value in accordance with ISO/IEC 19752 and continuous printing. Bertal yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/learnaboutsupplies. This will be product value in accordance with ISO/IEC 19752 and continuous printing. Bertal yield value in accordance with ISO/IEC 19752 and continuous printing. Bertal yield value in accordance with ISO/IEC 19752 and continuous printing. Bertal yield value in accordance with ISO/IEC 19752 and continuous printing. Bertal yield value in accordance with ISO/IEC 19752 and continuo



150-sheet input tray; 100-sheet output tray; **Duplex Options**: Manual duplex; **Auto Document Feeder Capacity**. 35 sheets; **Standard Paper Trays**: 1; **Input Capacities**: Up to 150 sheets standard; Up to 10**0utput Capacities**. Up to 100 sheets standard

